

AMENDMENTS TO THE CLAIMS

1. (Original) A microphone preamplifier, comprising
a differential input stage with a first and a second input terminal and an output stage with an output terminal; where the microphone preamplifier is integrated on a semiconductor substrate; and
a feedback circuit, with a low-pass frequency transfer function, coupled between the output terminal and the first input terminal and integrated on the semiconductor substrate;
where the second input terminal provides an input for a microphone signal.
2. (Original) A microphone preamplifier according to claim 1, wherein the differential input stage comprises an inverting input and a non-inverting input, wherein the non-inverting input is arranged to receive the microphone signal, and the inverting input is arranged to receive a feedback signal provided by the feedback circuit.
3. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit is a filter with a transfer function, in the frequency domain, with a zero and a pole; wherein the zero is located at a higher frequency than the pole.
4. (Previously presented) A microphone preamplifier according to claim 1, wherein the preamplifier has a transfer function, in the frequency domain, with a zero and a pole; wherein the pole is located in the range 0.1Hz to 50 Hz or 0.1Hz to 100Hz or 0.1 to 200Hz.
5. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit is a filter which, in the frequency domain, has a relatively high gain level below a transition frequency range and a relatively low gain level above the transition frequency range.
6. (Original) A microphone preamplifier according to claim 5, wherein the transition frequency range is located below a frequency of about 100 Hz.

7. (Original) A microphone preamplifier according to claim 5, wherein the transition frequency range is located below a frequency of 40 Hz.

8. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit is an active filter.

9. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit is a passive filter.

10. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit is configured with an active device which provides an ohmic impedance across a two-port circuit.

11. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit comprises a configuration with a first and a second active device and a current source, where the devices comprise a respective gate terminal, a source terminal and a drain terminal, and where the gate terminals are interconnected at a node connected to the current source and the drain terminal of the first device, and where the source terminals are interconnected, to provide the second device in a state where an ohmic resistance is provided between its drain and source terminal.

12. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit comprises a filter with an input port connected to a series connection of a first and second resistor which forms a resistor node at their interconnection, and connected to a series connection of a first and second capacitor which forms a capacitor node at their interconnection; and an output port at the capacitor node; wherein the resistor node and capacitor node are interconnected by an active device which provides an ohmic impedance across a two-port circuit.

13. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit comprises a source providing a DC offset.

14. (Previously presented) A microphone preamplifier according to claim 1, wherein the feedback circuit comprises a filter with a source that provides a DC offset.

15. (Previously presented) A microphone preamplifier according to claim 1, wherein a DC offset is provided at the first input of the preamplifier by a circuit configuration comprising a current source coupled, at the circuit node of the first input of the preamplifier, to an active device which provides an ohmic impedance across a two-port circuit.

16. (Original) A microphone preamplifier according to claim 15, wherein the active device constitutes a second device in a configuration with a first and the second active device and a current source, where the devices comprise a respective gate terminal, a source terminal and a drain terminal, and where the gate terminals are interconnected at a node connected to the current source and the drain terminal of the first device, and where the source terminals are interconnected, to provide the second device in a state where an ohmic resistance is provided between its drain and source terminal.

17. (Original) A microphone preamplifier according to claim 1, wherein the differential input stage comprises a first and second current path for the respective differential inputs, and wherein a DC offset is provided by establishing different DC currents through the first and second current path of the differential input stage.

18. (Previously presented) A microphone preamplifier according to claim 1, wherein the preamplifier is configured to receive the microphone signal via an input bias element which has relatively high ohmic impedance when the microphone signal is relatively small in magnitude and relatively low ohmic impedance when the microphone signal is relatively high in magnitude.

19. (Original) A microphone preamplifier according to claim 18, wherein the bias element is configured by two cross-coupled diodes.

20. (Original) A microphone preamplifier according to claim 18, wherein the bias element is configured by two cross-coupled bipolar transistors.

21. (Original) A microphone preamplifier according to claim 18, wherein the bias element is configured by two cross-coupled Metal Oxide Semiconductor, MOS, devices.

22. (Previously presented) A microphone preamplifier according to claim 1, wherein the preamplifier is a differential amplifier which is configured to convert an input signal into a common mode signal for low frequencies and into a differential signal for audio frequencies.

23. (Previously presented) A microphone preamplifier according to claim 1, wherein a differential amplifier is configured as an instrumentation type amplifier with two inputs and a first and a second output, wherein the first and second input is arranged to receive a microphone signal, but wherein the inputs are coupled to receive the microphone signals substantially in phase at relatively low frequencies and substantially out of phase at relatively high frequencies.

24. (Previously presented) A microphone preamplifier according to claim 1, wherein a differential amplifier is configured to provide frequencies below an audio band as common mode signals and audio band signals as differential mode signals.

25. (Previously presented) A microphone preamplifier according to claim 1, wherein a phase shifter is coupled between inputs of the differential amplifier.

26. (Previously presented) A microphone preamplifier according to claim 1, wherein a phase shifter is cross coupled between an output of one side of the differential amplifier and an input of the opposite side of the differential amplifier.

27. (Previously presented) A microphone preamplifier according to claim 21, wherein a phase shifter is coupled between a signal node, substantially in phase with an input signal to the amplifier, and an input terminal of an opposite side of the differential amplifier.

28. (Previously presented) A microphone according to claim 1, comprising
a voltage pump integrated on the semiconductor substrate.

29. (Previously presented) A microphone according to claim 1, comprising an electret microphone configured to provide a microphone signal, responsive to a sound pressure on the electret microphone, to the microphone preamplifier.

30. (Previously presented) A microphone module according to claim 1, wherein the electret microphone is mounted inside a space formed by a cartridge, and wherein the microphone preamplifier is integrated within the microphone module.

31. (Previously presented) A microphone preamplifier according to claim 1, comprising a MEMS microphone member to provide a microphone signal, responsive to a sound pressure on the MEMS microphone, to the microphone preamplifier.

32. (Currently amended) A microphone preamplifier according to claim 29 31, wherein the MEMS microphone member and the microphone preamplifier are integrated on a semiconductor substrate.